

DF2550 & DFG2562

Mantel Enclosure Design: If not using a Dimplex mantel, the fireplace must be installed in an enclosure with the following MINIMUM internal/opening dimensions: 24 ½ inches (622 mm) wide x 18 ¼ inches (464 mm) high x 9 inches (229 mm) deep. Ensure that the firebox is installed on a solid flat surface. Clearance for air circulation beneath the fireplace insert is provided by two (2) rubber feet. Ensure that there is at least ¼" of clearance from the back of the firebox. Keep combustibles away from the unit using the enclosure dimensions.

⚠ WARNING: Ensure that the enclosure design allows for the firebox to be removed for any service or maintenance.

New Construction Enclosure Design: The fireplace must be installed in an enclosure with the following MINIMUM internal/ opening dimensions: 24 ½ inches (622 mm) wide x 18 ¼ inches (464 mm) high x 9 inches (229 mm) deep. Clearance for air circulation beneath the fireplace insert is provided by two (2) rubber feet. Ensure that there is at least ¼" of clearance from the back of the firebox. Keep combustibles away from the unit using the enclosure dimensions.

⚠ WARNING: Ensure that the enclosure design allows for the firebox to be removed for any service or maintenance.

Vented Air: The enclosure MUST NOT block the front top edge or the lower back louvers (see diagrams below), air is taken in from the back louvers and returned from the upper vent. The firebox may overheat if any of these vents are obstructed.

⚠ WARNING: The heater is hot when in use. To avoid burns, do not let bare skin touch hot surfaces. The trim around the heater outlet becomes hot during heater operation. Keep combustible materials, such as furniture, pillows, bedding, papers, clothes, and curtains at least 3 feet (0.9 m) from the front of the unit.

Power: The unit comes wired with a two prong power cord, which exits the lower rear/right side of the firebox. The firebox can also be wired directly to a 120V power supply.

Recommended Electrical Specifications

Volts	Wire Gauge	Fuse Rating	Rated Power	Full Power
120 V	14 Ga.	15 A	880 W	7.33 A

